

Changing a CCR Tree message

Use this procedure to change the recorded message for a Menu or an Information node.

- | | |
|---|--|
| <pre>Log: QUIT RETRY <u>OK</u></pre> | <p>1 Press [*][9][8][3].
Enter the System Administrator Mailbox number and password,
and then press <u>OK</u>.</p> |
| <pre>Admin MBOX AA <u>OTHR</u></pre> | <p>2 Press <u>OTHR</u>.</p> |
| <pre>Admin GLIST <u>CCR</u></pre> | <p>3 Press <u>CCR</u>.</p> |
| <pre>CCR Admin ADMIN</pre> | <p>4 Press <u>ADMIN</u>.</p> |
| <pre>CCR tree: RETRY <u>OK</u></pre> | <p>5 Enter the number of the CCR Tree that you want to change and press <u>OK</u>.</p> |
| <pre>Tree: x CHNG PRINT QUIT</pre> | <p>6 Press <u>CHNG</u>.</p> |
| <pre>Path: RETRY END <u>OK</u></pre> | <p>7 Enter the Path of the node you want to change and press <u>OK</u>.</p> |
| <pre>x xxxx CHNG ERASE <u>OK</u></pre> | <p>8 Press <u>CHNG</u>.</p> |
| <pre>Primary rec? REC PLAY NEXT</pre> | <p>9 Lift the handset and press <u>REC</u>. Do not use handsfree.
At the tone, record the primary language menu.</p> |
| <pre>Rec pri Prompt: RETRY <u>OK</u></pre> | <p>10 Press <u>OK</u> to end your recording.</p> |
| <pre>Accept Prompt? RETRY PLAY <u>OK</u></pre> | <p>11 Press <u>OK</u> to accept your recording.</p> |
| <pre>Alternate rec? YES NO</pre> | <p>12 Press <u>NO</u> if you do not want to record an alternate message
or
press <u>YES</u> to record an alternate message.</p> |
| <pre>Path: RETRY END <u>OK</u></pre> | <p>13 Press <u>END</u>.</p> |
| <pre>Tree: x SAVE PRINT QUIT</pre> | <p>14 Press <u>SAVE</u>.</p> |
| <pre>Save as tree x YES OTHR QUIT</pre> | <p>15 Press <u>YES</u>.</p> |
| <pre>Tree saved</pre> | <p>16 This display appears briefly.</p> |
| <pre>CCR Admin ADMIN</pre> | <p>17 Press [*] to end the session.</p> |