

## Changing a CCR Tree message

Use this procedure to change the recorded message for a Menu or an Information node.

- |  |   |
|--|---|
| Log:<br>QUIT RETRY <u>OK</u>   | 1 Press <u>☎</u> <u>9</u> <u>8</u> <u>3</u> .<br>Enter the System Administrator Mailbox number and password, and then press <u>OK</u> . |
| Admin<br>MBOX AA <u>OTHR</u>   | 2 Press <u>OTHR</u> .   |
| Admin<br>GLIST <u>CCR</u>  | 3 Press <u>CCR</u> .  |
| CCR Admin<br><u>ADMIN</u>  | 4 Press <u>ADMIN</u> .  |
| CCR tree:<br>RETRY <u>OK</u>   | 5 Enter the number of the CCR Tree that you want to change and press <u>OK</u> .  |
| Tree: x<br><u>CHNG</u> PRINT QUIT  | 6 Press <u>CHNG</u> .   |
| Path:<br>RETRY END <u>OK</u>   | 7 Enter the Path of the node you want to change and press <u>OK</u> .   |
| x<br><u>CHNG</u> ERASE <u>OK</u> <span style="float: right;">xxxx</span> | 8 Press <u>CHNG</u> .   |
| Primary rec?<br><u>REC</u> PLAY NEXT                                     | 9 Lift the handset and press <u>REC</u> . Do not use handsfree. At the tone, record the primary language menu.                          |
| Rec pri Prompt:<br>RETRY <u>OK</u>                                       | 10 Press <u>OK</u> to end your recording.   |
| Accept Prompt?<br>RETRY PLAY <u>OK</u>                                   | 11 Press <u>OK</u> to accept your recording.  |
| Alternate rec?<br>YES NO   | 12 Press <u>NO</u> if you do not want to record an alternate message or press <u>YES</u> to record an alternate message.                |
| Path:<br>RETRY <u>END</u> OK   | 13 Press <u>END</u> .   |
| Tree: x<br><u>SAVE</u> PRINT QUIT  | 14 Press <u>SAVE</u> .  |
| Save as tree x<br><u>YES</u> OTHR QUIT                                   | 15 Press <u>YES</u> .   |
| Tree saved   | 16 This display appears briefly.  |
| CCR Admin<br><u>ADMIN</u>  | 17 Press <u>☎</u> to end the session.   |